


# PARTS CATALOGUE/TECHNICAL GUIDE

## Cal. V14JA

### [SPECIFICATIONS]

| Item                            |                      | Cal. No. | V14JA   |
|---------------------------------|----------------------|----------|---|
| Movement                        |                      |          | <br><div>(x 1.0)</div>  |
| Movement size                   | Outside diameter     |          | ø25.0 mm<br>24.0 mm between 6 o'clock and 12 o'clock sides<br>21.3 mm between 3 o'clock and 9 o'clock sides   |
|                                 | Casing diameter      |          | ø24.0 mm<br>23.3 mm between 6 o'clock and 12 o'clock sides<br>19.3 mm between 3 o'clock and 9 o'clock sides   |
|                                 | Height               |          | 3.5 mm (Including the battery portion)  |
| Time indication                 |                      |          | 3 hands   |
| Driving system                  |                      |          | Step motor (Load compensated driving pulse type)  |
| Additional mechanism            |                      |          | <ul style="list-style-type: none"> <li>• Solar power system</li> <li>• Overcharge prevention function</li> <li>• Energy depletion forewarning function</li> <li>• Quick-start function</li> <li>• Electronic circuit reset switch</li> <li>• Train wheel setting device</li> <li>• Day and date calendar function (Day and date hands)</li> <li>• Instant setting device for date calendar</li> <li>• 24-hour indication system (24-hour hand)</li> </ul> |
| Loss/gain                       |                      |          | Monthly rate at normal temperature range: less than 20 seconds  |
| Regulation system               |                      |          | Nil   |
| Measuring gate by quartz tester |                      |          | Use 10-second gate.   |
| Power supply                    | Power generator      |          | Solar power system  |
|                                 | Rechargeable battery |          | Titanium-lithium ion rechargeable battery   |
| Operating voltage range         |                      |          | 0.45 ~ 2.20 V   |
| Expected life per charge        |                      |          | From full charge to stoppage: Approx. 6 months  |
| Jewels                          |                      |          | 2 jewels  |

SEIKO CORPORATION

Disassembling procedures Figs. : ① → ④⑧


Reassembling procedures Figs. : ④⑧ → ①

Lubricating: Types of oil

● Moebius A


Oil quantity

○ Normal quantity




|  |                                  |          |
|--|----------------------------------|----------|
|  | 0022 247                         |          |
|  | • Battery lead terminal screw    | (1 pc.)  |
|  | • Circuit block cover screw      | (2 pcs.) |
|  | 0012 354                         |          |
|  | • Calendar mechanism plate screw | (2 pcs.) |
|  | • Hour wheel guard screw         | (2 pcs.) |

○ ➡ Please see the remarks on the following pages.  
(Lubricating of some parts is shown in “II. REMARKS ON DISASSEMBLING AND REASSEMBLING”)



○ ➞ Please see the remarks on the following pages.  
(Lubricating of some parts is shown in "II. REMARKS ON DISASSEMBLING AND REASSEMBLING")



○ ➞ Please see the remarks on the following pages.  
(Lubricating of some parts is shown in "II. REMARKS ON DISASSEMBLING AND REASSEMBLING")

## Remarks:

- ⑧ Solar cell unit (with holding ring for dial) 4020 589

As the solar cell unit is set to the holding ring for dial with glue, its type is determined based on the design of cases. Check the case number and refer to "PULSAR Casing Parts Catalogue" to choose a corresponding solar cell unit.


- ④③ Winding stem 0351 892

The type of winding stem is determined based on the design of cases. Check the case number and refer to "PULSAR Casing Parts Catalogue" to choose a corresponding winding stem.

# TECHNICAL GUIDE

- The explanation here is only for the particular points of Cal. V14JA.
- For the repairing, checking and measuring procedures, refer to the "TECHNICAL GUIDE, GENERAL INSTRUCTIONS".

## I. STRUCTURE OF THE CIRCUIT BLOCK




## II. REMARKS ON DISASSEMBLING AND REASSEMBLING

### ① ~ ⑥ Hands

#### • How to install

Place the movement directly on a flat metal plate or the like to install the hands. In doing so, check that the spring portion of the circuit block cover is not pressed down.




#### • Hand installation procedure

- 1) Install the date and day hands at desired marker positions, respectively.
- 2) Pull out the crown to the second click, and turn it clockwise until the date hand shifts.
- 3) Install the 24-hour hand so that it exactly indicates "24" on the 24-hour scale. In doing so, take care not to press down on the movement too hard.
- 4) Install the hour, minute and second hands in the same manner as you do with conventional watches.
- 5) Check that all the hands are fixed properly in position.

### ⑦ Dial

#### • How to install


Set the notched portions of the dial to the guide posts at the 4 o'clock and 10 o'clock sides of the solar cell unit, and check that the dial is fixed in position.



## 8 Solar cell unit

### • How to remove



- The solar cell unit is fixed by two hooking portions at the 12 o'clock and 6 o'clock sides.
- Insert the tip of a screwdriver into a gap between the hooking portion and main plate as shown in the illustration, and then, turn the screwdriver in the direction of the arrow to release the hooking portion from the main plate.



### • How to install

- Set the hooking portions at the 12 o'clock and 6 o'clock sides to the main plate.
- Gently push the solar cell unit above the hooking portions so that they catch the main plate securely.


- Notes:**
- When installing the solar cell unit, take care not to damage or deform the solar panel.
  - After installing the solar cell unit, check that both the hooking portions catch the main plate securely.
  - If the solar panel is soiled, gently wipe it with a soft chamois or the like soaked with alcohol.



## 12 Calendar mechanism plate


### • Setting position

Refer to the illustration below to check where to install the respective wheels.



### • How to install

- 1) Set the date jumper to the date star, and then have the hooking portion "A" catch the main plate.
- 2) Set the day jumper to the day wheel, and then have the hooking portion "B" catch the main plate.
- 3) Tighten the two calendar mechanism plate screws.



### • Lubricating


Refer to the illustrations above to lubricate the date and day jumpers.



## 14 Date corrector setting wheel

### • How to install


Set the date corrector setting wheel in the direction as shown in the illustration at right, taking care not to set it upside down.



## 15 Intermediate date wheel

### • How to install


Set the intermediate date wheel in the direction as shown in the illustration at right, taking care not to set it upside down.



## 16 Day driving wheel



## 17 Date driving wheel

Cal. V14JA watches use two different driving wheels to turn the date and day hands. It is necessary, therefore, to adjust the engagement of the wheels so that the date and day hands shift properly.



### • How to install the date and day driving wheels for proper engagement

- 1) Install the date driving wheel so that its claw overlaps the guide post "A" of the main plate as shown in the illustration below.
- 2) While checking that the date driving wheel does not move, install the day driving wheel so that its claw overlaps the guide post "B" of the main plate as shown in the illustration below.



## 26 Rechargeable battery unit


### • How to remove

- Remove the battery lead terminal screw, and then pry up the "A" portion in the illustration with tweezers to remove the rechargeable battery unit.

### • How to install

- Set the "B" portion of the battery lead terminal to the guide hole of the main plate, and then push the center portion of the rechargeable battery unit (the "C" portion in the illustration) to fix it in position.



- Notes:**
- Be sure to observe the correct polarity of the rechargeable battery unit. The (–) side has the lead terminal.
  - Handle the rechargeable battery unit with care so as not to short-circuit its (+) and (–) terminals.



## 30 Train wheel bridge

### • Setting position

Refer to the illustrations below to check where to install the respective wheels.




## 37 Train wheel setting lever

## 41 Setting lever

## 42 Yoke


### • Setting position

Refer to the illustration at right.



## ④3 Winding stem

- The first intermediate wheel for calendar correction has some elasticity in the contact with the winding stem so that it can be easily fixed.
- Push in the winding stem straight toward the center of the main plate.



## III. VALUE CHECKING

### • Coil block resistance


1.8K $\Omega$  ~ 2.2K $\Omega$

### • Current consumption

|                             |   |  |
|-----------------------------|---|--|
| For the whole movement      | : | Less than 0.8 $\mu$ A (with voltage supplied from a battery) |
| For the circuit block alone | : | Less than 0.4 $\mu$ A (with voltage supplied from a battery) |

### <Measuring the current consumption for the whole movement>

- 1) Remove the solar cell unit.
- 2) Remove the rechargeable battery unit and tighten the battery lead terminal screw.
- 3) Connect the tester as shown in the illustration.
- 4) Start the measurement 30 seconds to 2 minutes after connecting the tester, checking that a stable measurement is obtained.



## <Measuring the current consumption for the circuit block alone>

- Connect the tester to the input terminals (+) and (–) of the circuit block, and wait for 30 seconds to 2 minutes before starting the measurement, checking that a stable measurement is obtained.

**Remarks:** When the current consumption exceeds the standard value for the whole movement but is within the standard value range for the circuit block alone, the watch is generating a driving pulse to compensate for the heavy load that may be applied to the gear train, etc.  
In this case, overhaul and clean the movement parts and then measure current consumption for the whole movement again.

## • Output voltage for the solar cell unit

Output voltage when the watch is placed at a distance of 5cm under a fluorescent light of 15 to 20 watts: More than 2.3V.


- Use either of the following two methods to measure the output voltage for the solar cell unit.
  1. Measurement of the output voltage for the watch
  2. Measurement of the output voltage for the solar cell unit alone

**Remarks:** If the output voltage for the watch is less than the specified value, measure the output voltage for the solar cell unit alone.


If the output voltage for the solar cell unit alone exceeds the specified value, check the solar cell lead terminal for conductivity, etc.

## <Measuring the output voltage for the watch>

- 1) Set the dial to the solar cell unit.
- 2) Make sure that the rechargeable battery unit is not installed into the watch.
- 3) Pull out the crown to the second click and reset the circuit.
- 4) Connect the tester as shown in the illustration.




- 5) Place the watch at a distance of 5cm under a fluorescent light of 15 to 20 watts, exposing the dial side to the light, and then measure the output voltage.




## <Measuring the output voltage for the solar cell unit alone>

- 1) Set the dial to the solar cell unit.
- 2) Connect the tester as shown in the illustration.



- 3) Place the solar cell unit at a distance of 5 cm under a fluorescent light of 15 to 20 watts, exposing the dial side to the light, and then measure the output voltage.




## • Checking the quick-start function

The quick-start function can be checked only when the rechargeable battery voltage is less than 0.9V. Before checking the function, therefore, be sure to measure the voltage. (Refer to step 1 in "• Checking the recharging function".)

## <Checking procedure>

- After checking that the watch stops operating, place the watch at a distance of 50cm under a fluorescent light of 15 to 20 watts, exposing the dial side to the light. Then, check if the second hand starts moving at 2-second intervals within 10 seconds.




## • Checking the recharging function

A conventional method of checking the recharging function is to check the difference of the rechargeable battery voltage between before and after a recharge.

### <Checking procedure>


- 1) Apply the probes of the tester as shown in the illustration to measure the voltage of the rechargeable battery before recharge.




- 2) Place the watch at a distance of 5cm under a fluorescent light of 15 to 20 watts, and charge it for 30 minutes.

### Remarks:

- Be sure to use a fluorescent light to charge the watch, as light sources generating heat may cause damage to the watch. To charge the watch efficiently, place it under the center of the fluorescent tube.
- While charging the watch, make sure that the watch temperature does not exceed 50°C.



- 3) After recharging for 30 minutes, apply the probes of the tester in the same manner as in step 1) above, and measure the rechargeable battery voltage while keeping the watch exposed to the light.



- 4) Refer to the table below to determine whether the recharging function is normal or not.


### [Guideline for the quality of the recharging function]

| Voltage before recharge | Criteria for recharging quality   |
|-------------------------|---|
| 0.5 ~ 1.00V             | The battery is normal if the rechargeable battery voltage obtained after recharge is more than 1.1V.    |
| 1.01 ~ 1.30V            | The battery is normal if the rechargeable battery voltage has increased more than 0.03V after recharge. |

\* The above criteria are applicable only when the rechargeable battery voltage before recharge is within the range between 0.5V and 1.3V.

## • Remarks on measuring the time accuracy

- Before measuring the time accuracy, be sure to install the solar cell unit.
- If it is necessary to measure the accuracy while the solar cell unit is not installed and a stable measurement cannot be obtained, place the watch on the microphone of the quartz tester and leave it untouched for more than 2 minutes. Then, measure the accuracy again.



## • Guideline of charging time

| Illumination (lux) | Light source               | Environment       | Time required for full charge | Time required for 1-second intervals * | Time required to maintain one-day usage |
|--------------------|----------------------------|-------------------|-------------------------------|--|---|
| 500                | 60-watt incandescent light | Distance of 60 cm | 250 hours                     | 15 hours                               | 60 minutes                              |
| 700                | Fluorescent light          | Office, overhead  | 175 hours                     | 11 hours                               | 50 minutes                              |
| 1,000              | 30-watt fluorescent light  | Distance of 70 cm | 120 hours                     | 6 hours                                | 30 minutes                              |
| 3,000              | 30-watt fluorescent light  | Distance of 20 cm | 40 hours                      | 2 hours                                | 10 minutes                              |
| 5,000              | 30-watt fluorescent light  | Distance of 12 cm | 22 hours                      | 80 minutes                             | 6 minutes                               |
| 10,000             | 30-watt fluorescent light  | Distance of 3 cm  | 10 hours                      | 30 minutes                             | 3 minutes                               |
| 10,000             | Sun                        | Cloudy weather    | 10 hours                      | 30 minutes                             | 3 minutes                               |
| 100,000            | Sun                        | Fair weather      | 3 hours                       | 8 minutes                              | 1 minute                                |

- The above table provides only a general guideline, and the actual charging time may differ from model to model.

\* The values in this column represent the charging times required until the second hand moves constantly at 1-second intervals after the watch starts operating with the second hand moving at 2-second intervals. Even if the watch is not charged for the time specified in the column, the second hand may temporarily move at 1-second intervals. But, it will soon resume moving at 2-second intervals, and therefore, charge the watch for more than the specified period.

### [Caution for charging]

- To prevent damage to the watch caused by heat from a light source, make sure that the watch temperature does not exceed 50°C while charging the watch.